# 150 Watt Power Inverter 12 Volt

PWRINV150W

**Features**:Powers laptops camcorders small TV's games and much more. Now with thermal fan.

- 150W continuous power
- Modified sine wave
- Green LED on front panel to confirm power on
- Red LED on front panel to warn of a faulty condition
- Dual ac receptacles
- Dual USB ports
- On/off switch
- Over Temperature protection
- Over Load protection
- Noise free operation.
- Includes a thermal cooling fan.
- Enclosed cigarette lighter connections with built in fuse
- ac output short circuit protection
- Auto reset on most fault conditions
- Aluminum case for optimal cooling
- Instruction manual
- Free tech support
- 1 Year Warranty

**Specifications:**

- Continuous output power: 150 Watts
- Surge power capability (peak power): 300 Watts
- dc input / operating voltage: 10 to 16 Volts
- Output voltage: 120 Volts ac
- Output wave form: modified sine wave
- Output frequency: 60 Hz
- Battery low voltage alarm: 10.5 +/- 0.5 Volts
- Battery low voltage shutdown: 10.0 +/- 0.5 Volts

- Maximum efficiency: 90%
- No load minimum operating temperature: -15 degrees Celsius
- Full load maximum operating temperature: 55 +/- 5 degrees Celsius (automatic shutdown)
- AC Output Socket Type: dual Type 2 -3 prong
- 30 amp spade fuse
- .3 amps no load draw
- High input voltage protection: 16V
- Low input voltage shutdown: 10V
- External fuse protection
- Product size (L x W x H): 5.59”X 4.33”X 1.89”
- Weight: 13 oz