




	1202	1203	1505	8074	8174	8488	8588
Style	360 Panel System		360 Panel System	Traditional Metal		Traditional Metal	
Total Positions	Main + 6 positions		Main + 6 positions	Main + 8 positions		Main + 8 positions	
A-Series Circuit Breakers	Main, 30A (7414) 6 Branch, 15A (7403)	Main, 16A (7412) 6 Branch, 8A (7401)	Main, 30A (7414) 6 Branch, 15A (7403)	Main, 30A (7238) 5 Branch, 15A (7210)	Main, 16A (7294) 5 Branch, 8A (7299)	Main, 30A (7238) 5 Branch, 15A (7210)	Main, 16A (7294) 5 Branch, 8A (7299)
Nominal Voltage	120V AC	230V AC	120V AC	120V AC	230V AC	120V AC	230V AC
Actuator Style	Flat Rocker		Flat Rocker	White Toggle		White Toggle	
AC Meter	--		M2 AC Multimeter (1838)	0-150V (8244) 0-50A (8246)	0-250V (8245) 0-50A (8246)	0-150V (9353)	0-250V (9354)
Insulating Back Cover	2 x 1331 sold separately (p. 150)		--	--		--	
Width x Height in (mm)	4.88 (123.83) x 7.75 (196.85)		4.88 (123.82) x 10.75 (273.05)	5.25 (133.35) x 11.25 (285.75)		5.25 (133.35) x 11.25 (285.75)	
Depth in (mm)	3.00 (76.20)		4.00 (101.60)	3.00 (76.20)		2.50 (63.50)	



	8406	8506	8485	8585	8076	8176
Style	Traditional Metal		Traditional Metal		Traditional Metal	
Total Positions	Main + 8 positions		Main + 11 positions		Main + 11 positions	
A-Series Circuit Breakers	Main, 30A (7238) 5 Branch, 15A (7210)	Main, 16A (7294) 5 Branch, 8A (7299)	Main, 30A (7238) 8 Branch, 15A (7210)	Main, 16A (7294) 8 Branch, 8A (7299)	Main, 30A (7238) 8 Branch, 15A (7210)	Main, 16A (7294) 8 Branch, 8A (7299)
Nominal Voltage	120V AC	230V AC	120V AC	230V AC	120V AC	230V AC
Actuator Style	White Toggle		White Toggle		White Toggle	
AC Meter	Digital Multimeter (8247)		--		0-150V (8244) 0-50A (8246)	0-250V (8245) 0-50A (8246)
Insulating Back Cover	--		--		--	
Width x Height in (mm)	5.25 (133.35) x 11.25 (285.75)		5.25 (133.35) x 11.25 (285.75)		10.50 (266.70) x 7.50 (190.50)	
Depth in (mm)	4.00 (101.60)		2.50 (63.50)		3.00 (76.20)	



	8407	8507	8464	8564	8465	8565
Style	Traditional Metal		Traditional Metal		Traditional Metal	
Total Positions	Main + 11 positions		Main + 14 positions		Main + 22 positions	
A-Series Circuit Breakers	Main, 30A (7238) 8 Branch, 15A (7210)	Main, 16A (7294) 8 - Branch, 8A (7299)	Main, 30A (7238) 8 Branch, 15A (7210)	Main, 16A (7294) 8 Branch, 8A (7299)	Main, 30A (7238) 13 Branch, 15A (7210)	Main, 16A (7294) 13 Branch, 8A (7299)
Nominal Voltage	120V AC	230V AC	120V AC	230V AC	120V AC	230V AC
Actuator Style	White Toggle		White Toggle		White Toggle	
AC Meter	Digital Multimeter (8247)		--		--	
Width x Height in (mm)	10.50 (266.70) x 7.50 (190.50)		10.50 (266.70) x 7.50 (190.50)		14.75 (374.65) x 7.50 (190.50)	
Depth in (mm)	4.00 (101.60)		2.50 (63.50)		2.50 (63.50)	